

















Kura X1

IP65 IK 06 1J xx3 CE UK ER	LED			COL.	CODE *	
	W	LM	REAL LM			
	3	180	150	 220-240V  REMOTE DRIVER INCLUDED	 LL14701W□□	
					 LL14701B□□	
	2	180	150	 700mA-3V	 LZ14701W□□	
					 LZ14701B□□	

* Complete the CODE OPTIC S | 18° M | 28° L | 52° E | 11 X 37° LED COLOUR N | 4000K 3 | 3000K 2 | 2700K

Codici LL: driver esterno IP20 | LL codes: external driver IP20 | Codes LL : alimentation externe IP20 | Códigos LL: Alimentación externa IP20









Kura X3

IP65 IK 06 1J xx3 CE UK ER	LED			COL.	CODE *	
	W	LM	REAL LM			
	7,5	540	510	 220-240V  REMOTE DRIVER INCLUDED	 LL14702W□□	
					 LL14702B□□	
	6	540	510	 700mA-9V	 LZ14702W□□	
					 LZ14702B□□	

* Complete the CODE OPTIC S | 18° M | 28° L | 52° E | 11 X 37° LED COLOUR N | 4000K 3 | 3000K 2 | 2700K

Codici LL: driver esterno IP20 | LL codes: external driver IP20 | Codes LL : alimentation externe IP20 | Códigos LL: Alimentación externa IP20

Kura X5

IP65 IK 06 1J xx3 CE UK ER	LED			COL.	CODE *	
	W	LM	REAL LM			
	12,5	900	840	 220-240V  REMOTE DRIVER INCLUDED	 LL14703W□□	
					 LL14703B□□	
	10	900	840	 700mA-15V	 LZ14703W□□	
					 LZ14703B□□	

* Complete the CODE OPTIC S | 18° M | 28° L | 52° E | 11 X 37° LED COLOUR N | 4000K 3 | 3000K 2 | 2700K

Codici LL: driver esterno IP20 | LL codes: external driver IP20 | Codes LL : alimentation externe IP20 | Códigos LL: Alimentación externa IP20