



### Technical information:

|   |              |
|---|--------------|
| Brand                                     | SNAPPY       |
| Reference number                          | SNP30-24VF-3 |
| IP  | 20           |
| Power output                              | 30W          |
| Nominal DC output voltage<br>(under load) | 24V          |
| Nominal output current                    | 1,25A        |
| Input voltage range                       | 200-240V     |
| Frequency                                 | 50Hz         |
| Power factor ( $\lambda$ )                | 0,9          |
| Circuit breaker<br>B10 - C10 - B16 - C16  | 24-37-39-59  |
| Specifications                            | On-Off       |

### Dimension



### LED Controlgear Constant Tension

Parallel connection



### Warning!!!

Before connecting the ballast to the mains, ensure that the LEDs on the secondary are connected. Otherwise the lamp may not switch on.

